



IkaScope WS200

Ultra portable, one channel, 30 MHz, wireless oscilloscope.

Product status: Active.

03.JUN.2019

PRODUCT DATA SHEET AND USER MANUAL



IKALOGIC S.A.S.
19 Rue Columbia
87000 Limoges
FRANCE


Table of contents

IkaScope WS200 overview	2
Typical applications	2
Product highlights	2
⚠ Warning	3
Main characteristics	4
IkaScope WS200 Interfaces	4
Principle of operation	5
How does it work?	5
ProbeClick® technology	5
Connectivity options	5
Unpacking and first usage	5
Turning ON IkaScope	5
First connection	5
AP vs Station connection	6
LEDs behavior	6
Battery status LED	6
Wifi Status LED	6
Software Quick Start Guide	6
Measuring your first signal	6
Mechanical data	7
Safety information	7
General safety information	7
Lithium battery safety information	8
Certifications and regulations	9
What's in the box	9
Software technical requirements	10
Ordering information and customer support	10
Accessories and maintenance	11
Limited warranty & limitation of liability	11
Document Revisions	12

IkaScope WS200 overview

IkaScope WS200 is an ultra portable oscilloscope probe. It weighs less than 60g and is designed to fit perfectly in your hand. With a Wifi connection to a smartphone, a tablet or a computer, signals can be displayed and measurements can be easily made.

Patented ProbeClick® technology transforms the probe tip into an intelligent part of the oscilloscope: The probe detects when pressure is applied or released, allowing measurement to be automatically started and stopped without the need of traditional RUN/STOP button.



Typical applications

IkaScope is designed to be mobile, hence applications that require quick, on-the-field measurements are a perfect match for this technology.

- Onsite maintenance and inspection
- Isolated measurements
- Design troubleshooting
- Education and research
- Manufacturing industry
- Aerospace industry
- Automotive industry

Product highlights

- 200 MSPS for a 30 MHz bandwidth and 4 Kpts memory.
- Works on Windows, Linux, MacOS, Android and iOS.
- 1 week battery life (20 measurements per day).
- Patented ProbeClick® technology

Warning

Read "[Safety Information](#)" section carefully before using this instrument.

Main characteristics

Timing		
Sampling rate (MAX.)	200 MSPS (8 bits)	
Rise time (Calculated)	12 ns	
Input channels	1	
Sampling memory	4 Kpts ¹	
Bandwidth (-3 db) ²		MHz
100mV/div	50	
200mV/div	46	
500mV/div	37	
1V/div	40	
2V/div	38	
5V/div	38	
10V/div	30	
Waveform update rate	250 fps ³	
Time base accuracy	±100ppm	

Vertical		
Input impedance	1MΩ 14 pF	
Vertical resolution	8 bits	
Maximum input voltage	80 Vpp (±40V)	CAT I
Offset range		
≤ 1V/Div	± 20 V	
> 1V/Div	± 40 V	
DC vertical gain accuracy	±3% full scale	
All ranges		
DC vertical offset accuracy	± 3% of offset setting	
Coupling	DC / AC (True)	

¹ Sampling memory is divided into 4x1Kpts burst buffers allowing minimum dead time between 4 consecutive triggers

² According to measurements made on sample units taken from production batches.

Do not exceed ±40V between any measurement terminal and USB port.

³ Actual FPS (Frames Per Second) depend on Wifi network performance as well as display device performance.

General	
Input protection ²	253 VAC 1 minute
Input to USB galvanic isolation ²	1100 VAC 1 minute (production sample)
Built-in lithium battery	420 mAh
Communication interface	Wifi 802.11 b/g/n/e/i 2.4 GHz. Access point or Station
Operating, recharging and storage conditions	10°C to 40°C < 80%HR non-condensing Altitude < 2000m
Charging method	Micro USB port ⁴

IkaScope WS200 Interfaces



1. Probe tip
2. Ground lead connection
3. Status LEDs and charging port
4. Battery status LED
5. Wifi status LED
6. USB (micro-B) charging port.

⁴ The IKASCOPE should not be used during the battery charge in order to speed up the battery charge time.

Principle of operation

How does it work?

IkaScope can be seen as a wireless oscilloscope probe, that displays measured signals and is configured via remote screen (Tablet, smartphone or computer). Technically speaking, IkaScope WS200 integrates a full featured analog front end, a digital processing stage and a wifi module. First, measured signals are conditioned, then converted to digital values via a high speed 8-bits ADC. Finally, a digital processing stage streams the captured signal frames over a high speed wifi link.

ProbeClick® technology

IkaScope incorporates an intelligent probe tip (called ProbeClick®) that detects when pressure is applied. This allows important power saving since all power consuming circuitry is in stand-by when a measurement is not in progress. That same intelligent probe tip is used to turn ON IkaScope, which then turns OFF after 10 minutes of non activity. During that period IkaScope keeps wifi connexion active for optimal responsiveness when quick measurements need to be made.

Connectivity options

Since IkaScope is designed to be used in the office on the field, both Station and AP wifi modes are supported. In other words, IkaScope may as well connect to your office or home Wifi network (when configured to do so) or may create its

own Wifi Access Point to which another display device may connect.

Unpacking and first usage

IkaScope relies on a free application for display, analysis and configuration. You should first start by downloading and installing it on your favorite platform. Check ikalogic.com website for latest download link or search "ikascope" in the application store of your mobile device.

Turning ON IkaScope

After unpacking a new IkaScope, turn it ON by pressing the probe tip on any rigid surface for more than 1 second. At the very first usage, IkaScope will not have any configured Wifi networks in its memory, so it will automatically switch to AP (access point) mode. When IkaScope is correctly turned ON and operating in AP mode, Wifi status LED should be blinking in white color.

⚠ In some situations, IkaScope battery may be fully discharged. If that's the case, please connect your IkaScope to a USB port with the provided cable to recharge it. Refer to the LEDs Behavior section to ensure the battery is being correctly charged. Read the safety section first.

First connection

At this stage, you should configure your display device (Smartphone, tablet or computer) to connect to the Wifi network created by IkaScope. This network's SSID will start with "IKASCOPE" and will end with the serial number of your IkaScope device.

When your display device is connected to IkaScope's wifi network, you may launch IkaScope application and follow further instructions to display measured signals.

AP vs Station connection

Although IkaScope can be used in AP mode with its full performance, we recommend configuring IkaScope to connect to existing wifi networks. This way, it won't be necessary to change wifi settings of the display device for each and every usage.

LEDs behavior

There are 2 LEDs on the back of IkaScope probe. Refer to "[IkaScope WS200 interfaces](#)" chapter for more info about those LEDs.

Battery status LED

Normally, battery status LED is turned off. If the battery is empty (less than 20% capacity) it will blink in orange color. When you plug in a USB charger, it will either glow in orange to indicate that charging is in progress, or glow in green that charging is complete (battery is recharged to 100%).

Wifi Status LED


Wifi status led can show two colors: Blue or White, depending on the Wifi operating mode. White means AP mode (Access point, i.e., IkaScope created its own access point), while blue color means station mode.

If the LED is blinking it means no connection is made yet, when the LED is fixed, it means that a connexion was

established. By connection here, we mean a "network connection".

Software Quick Start Guide

Software follows a very similar user interface on all platforms composed of the following sections




1. IkaScope general menu that gives you access to connection options (mainly to connect the application to a specific IkaScope WS200 device)
2. Menus for Measurements, cursors, trigger and annotations.
3. AutoSet button
4. History feature, to restore previously measured signals.
5. Status and tips bar: Important information and hints are shown here.
6. Measured waveform.
7. Time/voltage gain and offset configuration.
8. Device status.

For detailed software manual, please check www.ikalogic.com.

Measuring your first signal

When IkaScope and the companion application are connected to the same network (either in AP or Station modes), you can start making measurements.

When both IkaScope and the application are correctly connected, the connection icon should be green as in the following screenshot.




Note: IkaScope device must be turned ON to be connected to a network. If all LEDs are switched OFF, please turn ON IkaScope by pressing on the probe tip for 1 second.

Finally, press IkaScope probe tip on the pad where an electric signal needs to be measured. You should hear a “click” sound, and feel a vibration in the device: This means that data is being streamed to the application. Keep the pressure on the tip until you see signals appearing in the application (This can take between 100 and 800 milliseconds).

Mechanical data

Weight: 60 gm (2.12 ounces)

Dimensions:



Safety information

General safety information

Complies with safety standards IEC NF/EN 61010-1: 2010, IEC NF/EN 61010-2-030 and UL 61010-1: 2015

To prevent possible electrical shock, fire, personal injury, or damage to the product, **read all safety information before you use the product.**

The following international symbols are used on the product and in this manual.

	Risk of Danger. Important information. See Manual.
	This product complies with the WEEE Directive (2002/96/EC) marking requirements. The affixed label indicates that you must not discard this electrical/electronic product in domestic household waste. Product Category: With reference to the equipment types in the WEEE Directive Annex I, this product is classed as category 9 Do not dispose of this product as unsorted municipal waste.
	Conforms to European Union directives.

Warning: To avoid electrical shock or fire:


- Carefully read all instructions.

- Use the product only as specified, otherwise the protection supplied by the product can be compromised.
- Do not use the product if it operates incorrectly.
- Before use, inspect device casing, probes, test leads and accessories for mechanical damage and replace if damaged.
- Never attempt to repair a defective device. Contact customer service.
- Do not use the product or its accessories in case of any damage.
- Remove all probes, test leads and accessories that are not in use.
- **Never use the device for measuring mains circuits.**
- Never use the device for measuring circuits which are not galvanically isolated from mains circuits.
- Do not touch electrical wires with bare hands.
- Keep away from children's sight or from animals.
- Do not expose to water, heat or moisture.
- Do not point probe tip toward body parts.
- **Do not connect the ground lead to voltages higher than $\pm 40V$ from earth ground.**
- **The electrical isolation between the USB port and the measurement ports is NOT designed to isolate from mains circuit.**
- **Do not apply more than the rated voltage ($\pm 40V$), between the terminals or between each terminal and USB port ground.**

- **Do not apply input voltages above the rating of the instrument ($\pm 40V$).**
- Measure a known voltage first to make sure that the product operates correctly.
- Do not work alone.
- Comply with local and national safety codes. Use personal protective equipment (approved rubber gloves, face protection, and flame resistant clothes) to prevent shock.
- Do not operate the product with covers removed or the case open. Hazardous voltage exposure is possible.
- Only recharge from a USB port.
- Do not use the device in wet or damp conditions, or around explosive gas or vapor.
- Do not use in a system in which the failure of the product might result in personal injury.

Lithium battery safety information

IkaScope WS200 contains a 420mAh lithium battery.

 **Warning:** To avoid electrical shock or fire:

- Never attempt to open an IkaScope WS200.
- Never attempt to replace the battery yourself. Contact customer service in case your battery needs replacement.
- Never recharge a device that shows signs of malfunctioning.
- **Never recharge IkaScope WS200 for more than 3 hours**

(disconnect the USB cable from USB port)

- Only use the USB cable provided by Ikalogic to recharge the device.
- Only connect the USB cable to a USB compliant port.
- Never recharge the device with a defective USB cable or charger.
- Do not store the device uncharged for long periods of time.
- Do not expose the device to temperatures beyond the range of 10°C to 40°C.
- Keep the device away from heat sources and direct sunlight.
- Do not subject device to impacts such as mechanical shocks or perforation.
- In case of accidental opening of the device, do not recharge or use the device and contact customer support.
- Never short-circuit the battery.
- Never overcharge the battery.
- The battery contains dangerous chemical components, that can cause burns or explode. In case of exposure to those chemical products, clean with water and get medical assistance immediately.
- Do not dispose of the battery as unsorted municipal waste.
- A failed battery pack should be disposed of in accordance with local regulations.

Certifications and regulations

EMC : IEC NF/EN 61326-1 (In high perturbed RF environment, the displayed signal may be altered during perturbation with self recovering) and complies with

Limit for class B digital device, pursuant to part 15 of the FCC rules.

IkaScope WS200 complies with the following regulations

- FCC (Part 15)
- CE
- ROHS
- REACH
- WEEE

IkaScope contains a lithium battery. Both the product and the battery were tested according to:

- PI965 AIR
- PI965 SEA
- PI967 AIR
- PI967 SEA
- UN38.3

IkaScope contains a Wifi module that complies with the following regulations

- CE1177
- FCC (USA)
- IC (Canada)
- GITEKI
- KCC

All test certificates can be provided upon request.

What's in the box

IkaScope WS200 is shipped with the following accessories:

- Ground connection probe.
- Protective cap.
- USB charging cable.
- Quick start guide.

Software technical requirements

Download the IkaScope app on www.ikalogic.com so you can use your device on your favorite platform.

Technical requirements:

Desktop computer with Wifi connection

- Windows 7/8/10 with OpenGL 2.0 or later (OpenGL ES excluded)
- Mac OS 10.9 with OpenGL 2.0 or later (OpenGL ES excluded)
- Ubuntu 14.04 with OpenGL 2.0 or later (OpenGL ES excluded)

Tablet/Smartphone

- Android 5.0 or later
- iOS 8 or later

Ordering information and customer support

For ordering information, please check for nearest distributor on www.ikalogic.com or contact us for any inquiry at contact@ikalogic.com.

Accessories and maintenance

Accessories and maintenance services (such as battery replacement and probe tip replacement) are available on our website: www.ikalogic.com or by contacting customer support.

Limited warranty & limitation of liability

Each Ikalogic product is warranted to be free from defects in material and workmanship under normal use and service. The warranty period is three years for the test tool and two year for its accessories (including the battery). This warranty extends only to the original buyer or end-user customer of an Ikalogic authorized reseller, and does not apply to fuses, disposable batteries or to any product which, in Ikalogic's opinion, has been misused, altered, neglected or damaged by accident or abnormal conditions of operation or handling.

THIS WARRANTY IS BUYER'S SOLE AND EXCLUSIVE REMEDY AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO ANY IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. IKALOGIC SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL OR CONSEQUENTIAL DAMAGES OR LOSSES, INCLUDING LOSS OF DATA, WHETHER ARISING FROM BREACH OF WARRANTY OR BASED ON CONTRACT, TORT, RELIANCE OR ANY OTHER THEORY.

Since some countries or states do not allow limitation of the term of an implied warranty, or exclusion or limitation of incidental or consequential damages, the limitations and exclusions of this warranty may not apply to every buyer. If any provision of this Warranty is held invalid or unenforceable by a court of competent jurisdiction, such holding will not affect the validity or enforceability of any other provision.

Document Revisions

- 03-June-2019: Updated safety related information.
- 28-May-2019: Updated safety related information.
- 27-March-2018: Corrected time base accuracy.
- 26-February-2018: Added software technical requirements section.
- 04-December-2017: Initial release of this datasheet.

This information is subject to change without notice. © Ikalogic SAS 2019, www.ikalogic.com